

UniMAX

Ring Tone Amplifier

The UniMAX Tone Alert and Ring Tone Amplifier is built to alert you when you have been paged. Place your pager or cellular phone in the UniMAX unit and its high volume audible alert will notify you of an incoming call or page.

The selectable alert tone will increase in volume in 15 second increments for one minute to reach maximum volume or until the reset button is pressed ensuring it will always catch your attention.

The UniMAX device is designed to work with most pagers and cellular phones while on AC or battery power.



Features

Indicator/Alert

- » Extra Loud Alert (>100dB)
- » Status Indicator
- » Low Battery Indicator
- » Selectable Alert Tones (10 tones)
- » Flexible Alert Time Settings
- » LED Flashing Light to Indicate a Pager or Call
- » Escalating Alert

And More

- » Indented Volume Control Knob
- » Low Power Consumption
- » Works with most pagers and cellular phones
- » Variety of power sources - AC Adapter and AA Alkaline Batteries

Specifications

Alert Tone	Max. >100 dB @ 12 in, Min. >70 dB @ 12 in
Battery Status Indication	Battery Full > LED On (green)
Battery Low	LED Flash (red)
Disposable Battery	AA Alkaline Battery x 3
Disposable Battery Life	estimated 3 weeks
Storage Temperature	4°F to 140°F
Operating Temperature	32°F to 122°F
Operating Humidity.....	< 85%
Weight	4.2 ounces
Size	3.77" W x 3.07" H x 2.00" D

Accessories

- » AC Power Adapter (standard)
- » Alpha Series Insert (standard)

CONTACT USA MOBILITY

E-mail: info@usamobility.com

Phone: (888) 576-1349